

OUTPUT VOLTAGE	50V (0~20%)			100V (0~20%)			250V (0~20%)				500V (0~20%)				1000V (0~20%)					
RANGE	0~ 20 MΩ	20~ 200 MΩ	200~ 500 MΩ	0~ 20 MΩ	20~ 200 MΩ	200 MΩ~ 1.00 GΩ	0~ 20 MΩ	20~ 200 MΩ	200 MΩ~ 250 GΩ	250 MΩ~ 2.50 GΩ	0~ 20 MΩ	20~ 200 MΩ	200~ 500 MΩ	500 MΩ~ 5.00 GΩ	0~ 200 MΩ	200~ 1000 MΩ	1.00~ 5.00 GΩ	5.00~ 10.00 GΩ	10.00~ 30.00 GΩ	30.00~ 100.00 GΩ
RESOLUTION	0.01 MΩ	0.1 MΩ	10 MΩ	0.01 MΩ	0.1 MΩ	10 MΩ	0.01 MΩ	0.1 MΩ	1 MΩ	10 MΩ	0.01 MΩ	0.1 MΩ	10 MΩ		0.1 MΩ	1 MΩ	0.1 GΩ	0.1 GΩ	0.1 GΩ	0.1 GΩ
TEST CURRENT	1mA@50K			1mA@100K			1mA@250K				1mA@500K				1mA@1000K					
ACCURACY	±(3%rdg+5dgt)		±(5%rdg +5dgt)	±(3%rdg+5dgt)		±(5%rdg +5dgt)	±(3%rdg+5dgt)			±(5%rdg +5dgt)	±(3%rdg+5dgt)		±(5%rdg+5dgt)		±(3%rdg+5dgt)		±(5%rdg +0.1 GΩ)	±(10%rdg +0.2GΩ)	±(20%rdg +0.2GΩ)	±(30%rdg +0.3GΩ)